

# Network Integration Guide

Schneider EVlink Smart WallBox

---



## 5. Local configuration setting


**IMPORTANT:** For instructions on how to open and operate this station, you must go to the manufacturer directly and request the latest installation manual. They will also provide you with information on where the SIM card slot is located.

### a. Unboxing the EVlink Wallbox



Unboxing EVSE : loosen screws (1) then open the main white cover (2) (3)

Unboxing EVSE (loosen screws in order to picture [1])  
▪ Open the main cover (1.) and fold back front panel (2.) to have access to the main charge controller



to have access to the main charge controller : 6 others point to unscrew (1) and fold back front panel (2)


## b. Pre-requisites for local configuration setting

<i>COMPUTER</i>	OS: Windows 10, 8, 7 etc./ MacOS/ Linux Current browser (IE, Edge, Firefox, Chrome, Safari etc.)
<i>SOFTWARE</i>	No additional or proprietary software needed.
<i>CONNEXION</i>	EVSE uses micro-/Type A-USB to access WebUI for initial configuration EVSE supports Ethernet with TCP/IP (via USB Ethernet dongle)
<i>TOOLS</i>	Flat head screw-driver for connection to grid (screw in) Allen key (4mm) for mounting/dis-mounting enclosure

## c. Access to WebUI

- Set your computer IP setting to :
  - IP assignment : Manual
  - IPv4 address : 192.168.0.88
  - IPv4 subnet prefix length : 24
  - IPv4 gateway : 192.168.0.255
- Connect to 192.168.0.102
  - Username : admin  
Password : ADMIN
- Configuration - General settings

- Charging station name → “Schneider\_EVlink”
- Station type → “Supervised”
- Authentication done by → “Supervision”
- Authentication strategy when communication lost → “Allow all badges”
- Front panel push button activated → “No”



#### ▪ Configuration - Supervision

- OCPP Version → “1.6”
- Supervision URL → <wss://ocpp-eu.chargepoint.com/open/1ocpp/j1.6>
- Charging station ID → <MAC ID>

present on MAC label, please enter it without colons !!


- Modem Schneider Electric presents → “on”
- Modem IP Address → “192.168.0.254”



Charging station ID is the MAC presents on the label with the QR Code - make sure you enter the MAC without colons !!

“0224B1EFFF00XX” and not “0224:B1E:FE00:XX”


<sup>1</sup> <http://eu.chargepoint.com/open/>



- Go to the top of the page and press “Save and reboot” and wait until station rebooted



- Check in “Maintenance” menu, tap “Report” whether OCPP connection to NOS is successfully established, export of report can be done also to keep track that the renetworking was successful.



### Limited Warranty Information and Disclaimer

The Limited Warranty you received with your charging station is subject to certain exceptions and exclusions. For example, your use of, installation of, or modification to, the ChargePoint® charging station in a manner in which the ChargePoint® charging station is not intended to be used or modified will void the limited warranty. You should review your limited warranty and become familiar with the terms thereof. Other than any such limited warranty, the ChargePoint products are provided "AS IS," and ChargePoint, Inc. and its distributors expressly disclaim all implied warranties, including any warranty of design, merchantability, fitness for a particular purposes and non-infringement, to the maximum extent permitted by law.

### Limitation of Liability

CHARGEPOINT IS NOT LIABLE FOR ANY DIRECT, INDIRECT, INCIDENTAL, SPECIAL, PUNITIVE OR CONSEQUENTIAL DAMAGES, INCLUDING WITHOUT LIMITATION LOST PROFITS, LOST BUSINESS, LOST DATA, LOSS OF USE, OR COST OF COVER INCURRED BY YOU ARISING OUT OF OR RELATED TO YOUR PURCHASE OR USE OF, OR INABILITY TO USE, THE CHARGING STATION, UNDER ANY THEORY OF LIABILITY, WHETHER IN AN ACTION IN CONTRACT, STRICT LIABILITY, TORT (INCLUDING NEGLIGENCE) OR OTHER LEGAL OR EQUITABLE THEORY, EVEN IF CHARGEPOINT KNEW OR SHOULD HAVE KNOWN OF THE POSSIBILITY OF SUCH DAMAGES. IN ANY EVENT, THE CUMULATIVE LIABILITY OF CHARGEPOINT FOR ALL CLAIMS WHATSOEVER RELATED TO THE CHARGING STATION WILL NOT EXCEED THE PRICE YOU PAID FOR THE CHARGING STATION. THE LIMITATIONS SET FORTH HEREIN ARE INTENDED TO LIMIT THE LIABILITY OF CHARGEPOINT AND SHALL APPLY NOTWITHSTANDING ANY FAILURE OF ESSENTIAL PURPOSE OF ANY LIMITED REMEDY.

### FCC Compliance Statement

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference when the equipment is operated in a residential installation. This equipment generates, uses, and can radiate radio frequency energy and, if not installed and used in accordance with the instruction manual, may cause harmful interference to radio communications.

Important: Changes or modifications to this product not authorized by ChargePoint, inc., could affect the EMC compliance and revoke your authority to operate this product.

Exposure to Radio Frequency Energy: The radiated power output of the 802.11 b/g/n radio and cellular modem (optional) in this device is below the FCC radio frequency exposure limits for uncontrolled equipment. The antenna of this product, used under normal conditions, is at least 20 cm away from the body of the user. This device must not be co-located or operated with any other antenna or transmitter by the manufacturer, subject to the conditions of the FCC Grant.

### ISED (formerly Industry Canada)

This device complies with the licence-exempt RSS standard(s) of Innovation, Science and Economic Development Canada (ISED).

Operation is subject to the following two conditions: (1) this device may not cause interference, and (2) this device must accept any interference, including interference that may cause undesired operation of the device.

Cet appareil est conforme aux flux RSS exemptés de licence d'Innovation, Sciences et Développement économique Canada (ISDE).

L'exploitation est autorisée aux deux conditions suivantes : (1) l'appareil ne doit pas produire de brouillage, et (2) l'utilisateur de l'appareil doit accepter.

Radiation Exposure Statement: This equipment complies with the IC RSS-102 radiation exposure limits set forth for an uncontrolled environment. This equipment should be installed and operated with a minimum distance of 20 cm between the radiator and your body.

Énoncé d'exposition aux rayonnements: Cet équipement est conforme aux limites d'exposition aux rayonnements ioniques RSS-102 Pour un environnement incontrôlé. Cet équipement doit être installé et utilisé avec un Distance minimale de 20 cm entre le radiateur et votre corps.

FCC/IC Compliance Labels Visit

[chargepoint.com/labels](http://chargepoint.com/labels).



[chargepoint.com/support](https://chargepoint.com/support)

09182024