

Re-Networking Station Manuals

Below are the stations supported by ChargePoint. Click on any picture to download the instruction manual for that station:

*General Note:

- For the OCPP ChargeBox ID in the manufacturers configuration, do **NOT** use special characters of the MAC address provided. Example:






Introduce: **0224B1FFFE0013AC** in station configuration instead of **0224:B1FF:FE00:13AC**





- SIM card APN: **cp-onramp-1.m2m** (no username / no password)





Backend Ocpp 1.6 Url for public connection are the following, unless specifically mentioned.



- FOR United States of America (US): <wss://ocpp-us.chargepoint.com/open/ocpp/j1.6>
- FOR Canada (CA): <wss://ocpp-ca.chargepoint.com/open/ocpp/j1.6>
- FOR European Countries (EU): <wss://ocpp-eu.chargepoint.com/open/ocpp/j1.6>





Charger	Region	Comments
ABB DC Terra & HVC 	US, CA, EU	Contact ABB to configure the station to ChargePoint specs with the ChargeBox ID found in the activation sticker
ADSTec 	EU, US	Station needs private url. FOR EU: <code>wss://ws-private.ocpp.chargepoint.net/open/ocpp/j1.6</code> FOR US: <code>wss://ws-private-us.ocpp.chargepoint.net/open/ocpp/j1.6</code>
ALFEN EVE DUAL PRO-LINE 	EU	Make sure that you download the root certificate via ACE Service Installer Station needs private url. FOR EU: <code>wss://ws-private.ocpp.chargepoint.net/open/ocpp/j1.6</code>



ALFEN EVE SINGLE PRO-LINE 	EU	<p>Make sure that you download the root certificate via ACE Service Installer</p> <p>Station needs private url.</p> <p>FOR EU: wss://ws-private.ocpp.chargepoint.net/open/ocpp/j1.6</p>
Alpitronic HYC 	US, CA, EU	<p>Contact Alpitronic to get instructions on how to configure the station</p> <p>US requires Ocpp 2.0 connection with the following url.</p> <p>FOR US: wss://ocpp-us.chargepoint.com/open/ocpp/j2.0</p>
Control Module EVSE 3704 	US, CA	<p>Contact CMI to configure the station with the correct URL and ChargeBox ID found in the activation sticker</p>
DELTA 25 kW 	US, CA, EU	<p>Contact Delta to get the installation manual and be trained for installation commissioning</p>

<p>EATON Green Motion Building</p> 	<p>EU</p>	<p>Contact Eaton/GreenMotion To receive the configuration guide</p>
<p>EFACEC</p>  <p>QC45</p>	<p>US, CA, EU</p>	<p>Contact EFACEC to obtain the EV Config manual and a log in. Then configure the station with the correct URL and ChargeBox ID found in the activation sticker</p>
<p>Freewire Boost 150 & 200</p> 	<p>US, CA, EU</p>	<p>Contact freewire to configure the station with the correct URL and ChargeBox ID found in the activation sticker</p>
<p>Hager Witty XEV</p> 	<p>EU</p>	<p>Be sure that station is already equipped with the optional 4G modem Sierra or Teltonika that can be installed inside the station or outside or equipped with the 4G sim KIT. Station also needs optional MID meter</p>

<p>Hager Witty Park</p> 	<p>EU</p>	<p>Be sure that station is already equipped with the optional 4G modem Sierra or Teltonika that can be installed inside the station or outside or equipped with the 4G sim KIT. Station also needs optional MID meter</p>
<p>IES KEYWATT</p> 	<p>US, CA, EU</p>	<ol style="list-style-type: none"> 1. Select the charger being configured. 2. On the left, select "Support Software". 3. Click on the manual for InTools. <p>Follow the manual to configure the station.</p>
<p>KEBA P30</p> 	<p>EU</p>	<p>Download the installation manual selecting your language If necessary, you can also download in the Updates section Firmware Update V3.10.28</p>
<p>Kempower</p> 	<p>EU, US</p>	<p>Contact Kempower to get a user account to Kempower cloud service and configure the station with the URL and ChargeBox ID found in the activation sticker</p>

<p>LEGRAND GREEN-UP PREMIUM</p> 	<p>EU</p>	<p>Station needs optional components:</p> <ul style="list-style-type: none"> - KIT COM 059056 - KIT RFID 059059 <p>4G modem from Teltonika recommended by Legrand</p>
<p>MENNEKES AMTRON PRO+</p> 	<p>EU</p>	
<p>MENNEKES AMTRON TWINCHARGE</p> 	<p>EU</p>	

MENNEKES AMEDIO PRO+ 	EU	
Power Electronics NB 120/240 	US, CA, EU	Contact Power Electronics to get manual on the Web Manager application to configure station
SCHNEIDER EV LINK SMART WALLBOX 	EU	<ol style="list-style-type: none"> 1. Go to document section 2. Download the commissioning guide
SCHNEIDER EV Link PRO AC 	EU	<ol style="list-style-type: none"> 1. Go to document section 2. Download the commissioning guide

<p>TRITIUM RT</p> 	<p>US, CA, EU</p>	<p>Contact Tritium to get the installation manual and be trained for installation commissioning</p>
<p>TRITIUM PK</p> 	<p>US, CA, EU</p>	<p>Contact Tritium to get the installation manual and be trained for installation commissioning</p>